

Celadon Inc.

RCV-5000 IR to RS-232 Output Table

Device: Faroudja NRS-DVI Digital Video Processor

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol

Infrared Code Format: NEC - Device ID: 7B02

Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description

Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver

RCV-5000 Data File: farou2_r.hex

Data: 19200 Baud, 8, N, 1, ASCII Output

Note: Header is NRS followed by comma to separate. Carriage return at end of string.

Switch pins 2 & 3 - need gender changer (male)

Faroudja NRS-DVI Function	Pronto Button	RCV-5000 Output
Input Aspect Ratio - 4x3	0	NRS,A0
Input Aspect Ratio - Letterbox	1	NRS,A1
Input Aspect Ratio - Anamorphic	2	NRS,A2
Power OFF	3	NRS,OFF
Power ON	4	NRS,ON
Pass Through Input - HDTV to RGB	5	NRS,PR
Video Input	6	NRS,V
YCrCb Input	7	NRS,X
S-Video Input	8	NRS,Y
Pass Through Input - Input to HDTV	9	NRS,EXT
Video Preset 1	10	NRS,P1
Video Preset 2	11	NRS,P2
Video Preset 3	12	NRS,P3
Video Preset 4	13	NRS,P4

Celadon, Inc.

50 Mitchell Blvd.

San Rafael, CA 94903

Tel: (415) 472-1177

Fax: (415) 472-1179

sales@celadon.com